

10000mAh Mi Power Bank 3 Ultra Compact User Manual · 1

Руководство пользователя Ультракompактного внешнего аккумулятора Mi 3 (10000 мА·ч) · 8

Manual de usuario de 10000mAh Mi Power Bank 3 Ultra Compact · 14

Mi 보조배터리3 10000mAh 울트라 콤팩트 사용 설명서 · 20

10.000 mAh Mi Powerbank 3 Ultrakompakt Benutzerhandbuch · 26

Manuel d'utilisation de 10000mAh Mi Power Bank 3 Ultra Compact · 32

Manuale utente 10000mAh Mi Power Bank 3 Ultra Compact · 38

10000 mAh Mi Taşınabilir Şarj Cihazı 3 Ultra Kompakt Kullanım Kılavuzu · 44

Посібник користувача Надкомпактний зовнішній акумулятор Mi 3 (10 000 мА·год) · 50

Mi دليل المستخدم الشاحن المتنقل متناهي الصغر 3 سعة 10000 مللي أمبير/ساعة من Mi · 56

10000 mAh Mi Powerbank 3 Ultracompact Gebruikershandleiding · 62



Read this manual carefully before use, and retain it for future reference.

Product Overview

Thank you for choosing 10000mAh Mi Power Bank 3 Ultra Compact. This product is small and portable, supporting a maximum of 22.5 W in two-way fast charging. Equipped with high-quality lithium polymer battery cells and a charging and discharging chip, the power bank performs excellently in terms of safety, efficiency, and compatibility.

USB-C Port (Input/Output) Micro-USB Port (Input)

USB-A Port (Output) Battery Level Check Button

USB-A Port (Output) Battery Level Indicator



Notes:

The battery level check button is not a power button.

The power bank detects charging and discharging automatically.

Safety: This power bank is equipped with multiple safeguarding technologies to prevent overcharging, over-discharging, overheating, and short circuits in any working condition.


Fast Charging: USB-A single port supports 5 V/2.4 A, 9 V/2.5 A Max., 12 V/1.85 A Max. fast charging mode. USB-C single port supports 5 V/3 A, 9 V/2.5 A Max., 12 V/1.85 A Max. fast charging mode.

Compatibility: The built-in USB charge controller is compatible with most smart devices including smartphones, and tablets.

Quality: High-quality lithium polymer battery cells and a durable charging and discharging chip.

Charging

To charge the power bank, connect a Mi power charger and charging cable to its USB-C or Micro-USB port. The indicator shows the following charging status:



Battery Level	LED1	LED2	LED3	LED4
0-25%	Blinking	Off	Off	Off
25-50%	On	Blinking	Off	Off
50-75%	On	On	Blinking	Off
75-99%	On	On	On	Blinking
Fully Charged	On	On	On	On
Charging Error	Blinking	Blinking	Blinking	Blinking

Discharging

To charge devices via the power bank, connect the charging cable to the device and the power bank's USB-A or USB-C port. The indicator shows the following discharging status:

Battery Level	LED1	LED2	LED3	LED4
Undervoltage	Off	Off	Off	Off
0-25%	Blinking	Off	Off	Off
25-50%	Blinking	Blinking	Off	Off
50-75%	Blinking	Blinking	Blinking	Off
75-100%	Blinking	Blinking	Blinking	Blinking

* Low-current discharge: When the power bank is not charging, double press the battery level check button to enter the low-current discharge mode. This mode can be used to charge low-current devices such as Bluetooth headphones and smart bands. The indicator lights will turn on one by one to indicate the power bank is in low-current discharge mode. Simply press the button again to exit this mode. The power bank will automatically exit this mode after two hours.

Warnings

Improper use may result in battery failure, overheating, and even fire or explosion. To ensure your safety and minimize the risk of personal injury and property damage, please observe the following precautions:

- This power bank is not a toy. Please keep it away from children. Do not let children use or play with this power bank in order to avoid accidents.
- When charging this power bank, make sure you use a charger that complies with the local safety standards to prevent electric shocks or cause damage to the battery.
- Do not expose this power bank to pressure, impact, strong vibrations, or liquids. Any of these occurrences may lead to a short circuit or cause damage to the battery or electrical circuit. If this happens, stop using the power bank immediately, and dispose of it properly.
- When the power bank becomes swollen, deformed, starts to leak, or its capacity is significantly reduced, please stop using it immediately and dispose of it in a proper manner.
- Do not charge or discharge this power bank in places where its heat dissipation may be affected, such as in the pocket of your pants, a closed bag, or on a bed or sofa. Ensure the power bank is not covered by clothing, pillows, bedding, or other miscellaneous items during its working. When using the power bank to charge devices including phones for an extended time, do not stack them together to ensure better heat dissipation.
- Do not disassemble, puncture, strike, or short circuit this power bank. Never expose it to liquids, fire, and other heat sources such as stoves, heaters, or environments with ambient temperatures higher than 60°C (140°F).
- When it is hot, do not leave this power bank in a car or places that are exposed to direct sunlight.
- This power bank contains a lithium polymer battery. Opening the casing is strictly prohibited so as to avoid battery damage or safety hazards.

Precautions

- Please fully charge this power bank before using it for the first time.
- Use a qualified charger and a USB cable (Mi brand products are recommended) when charging the power bank or using it to charge other devices.
- When charging this power bank, do not leave it unattended for a long time. Unplug it from the power supply before going out.
- Once this power bank is fully charged or fully charges the smart devices, unplug the charging cable in a timely manner to prevent damage.
- If the battery level indicator does not light up after pressing the button, it may be because the power bank is in protective mode. Try plugging in an external charger will restore the power bank.
- When not using this power bank for a long time, store it in a cool and dry environment and keep its battery level in the range of about 25–50%. For long-term storage, do not fully charge the power bank or leave the battery level empty to avoid reducing its battery life.

Illustrations of the product, accessories, and user interface in the user manual are for reference purposes only. The actual product and functions may vary due to product enhancements.

Specifications

Model: PB1022ZM Battery Type: Lithium Polymer Battery
Cell Capacity: 10000 mAh, 3.7 V, 37 Wh Rated Capacity: 5500 mAh (5 V/3 A)
Input Port: USB-C/Micro-USB Output Port: USB-A/USB-C
Input: (USB-C) 5 V \equiv 3 A, 9 V \equiv 2.5 A
(Micro-USB) 5 V \equiv 2 A, 9 V \equiv 2 A
Output: 22.5 W Max. (Triple-port) 5 V \equiv 3 A
(USB-A) 5 V \equiv 2.4 A, 9 V \equiv 2.5 A Max., 12 V \equiv 1.85 A Max.
(USB-C) 5 V \equiv 3 A, 9 V \equiv 2.5 A Max., 12 V \equiv 1.85 A Max.
Operating Temperature: 5°C to 35°C
Item Dimensions: 90 × 63.9 × 24.4 mm
Charging Time: Approx. 3.5 hours (PD 24 W charger* or above, with a USB-C to USB-C charging cable)
Approx. 6 hours (5 V/2 A charger*, with the charging cable included)
*Charger is not provided with power bank.

EU Declaration of Conformity



The manufacturer hereby, declares that this equipment is in compliance with the applicable Directives and European Norms, and amendments. The full text of the EU declaration of conformity is available at the following internet address:
<http://www.mi.com/global/service/support/declaration.html>

WEEE Information



All products bearing this symbol are waste electrical and electronic equipment (WEEE as in directive 2012/19/EU) which should not be mixed with unsorted household waste. Instead, you should protect human health and the environment by handing over your waste equipment to a designated collection point for the recycling of waste electrical and electronic equipment, appointed by the government or local authorities. Correct disposal and recycling will help prevent potential negative consequences to the environment and human health. Please contact the installer or local authorities for more information about the location as well as terms and conditions of such collection points.

Federal Communications Commission Supplier's Declaration of Conformity

This supplier's declaration of conformity is hereby for
Product: 10000mAh Mi Power Bank 3 Ultra Compact
Model Number(s): PB1022ZM
Brand/Trade: Mi

We declare that the above mentioned device has been tested and found in compliance with CFR 47 Part 15 Regulation.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference,
- (2) This device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a

Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Responsible Party – U.S. Contact Information

Company: Tekmovil LLC
Address: 601 BRICKELL KEY DR #723 MIAMI, FL 33131
Country: U.S.A.
Telephone No.: +1 (312) 282-5246
Internet contact information: kim.peterson@tekmovil.com

Representative of Responsible Party for SDoC

Company: Zimi Corporation
Address: A913, No. 159 Chengjiang Road, Jiangyin, Jiangsu, China
Country: P.R.C
Telephone No.: +86 (0)25 8715 6360

Anti-counterfeit Label Instructions

Each 10000mAh Mi Power Bank 3 Ultra Compact comes with an anti-counterfeit label on the outer package. To check the authenticity of the product, scratch the anti-counterfeit coating, and then enter the security code on chaxun.mi.com.



Anti-counterfeit Label



Scratched-off Coating

For further information, please go to www.mi.com

Manufactured for: Xiaomi Communications Co., Ltd.
Manufactured by: Zimi Corporation
(a Mi Ecosystem company)
Address: A913, No. 159 Chengjiang Road, Jiangyin, Jiangsu, China